

Features

- ▶ Supports 2 lighting lines with 127 points per line
- ▶ Slim profile - only 100 mm deep
- ▶ Robust design

**Description**

The EL-2 emergency light control panel features two lines, each line can accommodate 127 FIREscape devices. The EL-2 supplies the operational voltage to the light units during normal conditions, whilst also completing the continuous testing and monitoring of the equipment on the system.

All monitored event information is saved in the memory of the control panel, and this can be accessed by a connected EL-KP key pad

Specification

| | |
|----------------------------------|----------------------------------|
| Number of lights/signs supported | 254 |
| Connection voltage | 35 VAC (222 VA) |
| Nominal voltage | 12 VDC |
| Internal battery capacity | 7.2 Ah |
| I/O outputs | 2 relay outputs |
| Modem/PC connection | RS-232 |
| User panel connection | RS-485/9600 baud |
| Event memory | 500 events |
| Dimensions (mm) | 295W x 475H x 100D |
| Material/Colour | Sheet steel, powder-coated/White |
| Weight including batteries (kg) | 8 |

NOTE: Must be used in conjunction with the EL-35V Transformer